



7027

**BEAM POWER TUBE***For high-fidelity audio-amplifier applications*

7027

**GENERAL DATA****Electrical:**

Heater, for Unipotential Cathode:

Voltage . . . . . 6.3 . . . . . ac or dc volts

Current . . . . . 0.9 . . . . . amp

Direct Interelectrode Capacitances:<sup>0</sup>Grid No.1 to plate. . . . . 1.5  $\mu$ fGrid No.1 to cathode & grid No.3,  
grid No.2, and heater . . . . . 10  $\mu$ fPlate to cathode & grid No.3,  
grid No.2, and heater. . . . . 7.5  $\mu$ f**Characteristics, Class A<sub>1</sub> Amplifier:**

Plate Voltage . . . . . 250 volts

Grid-No.2 (Screen-Grid) Voltage . . . . . 250 volts

Grid-No.1 (Control-Grid) Voltage . . . . . -14 volts

Plate Resistance (Approx.) . . . . . 22500 ohms

Transconductance. . . . . 6000  $\mu$ mhos

Plate Current . . . . . 72 ma

Grid-No.2 Current . . . . . 5 ma

**Mechanical:**

Operating Position. . . . . Any

Maximum Overall Length. . . . . 4.62"

Maximum Seated Length . . . . . 4.06"

Maximum Diameter. . . . . 1.63"

Bulb. . . . . T12

Base. . . . . Small-Wafer Octal 8-Pin  
with Sleeve (JETEC No.B8-191)

Basing Designation for BOTTOM VIEW. . . . . 8HY


Pin 1-Grid No.2

Pin 2-Heater

Pin 3-Plate

Pin 4-Grid No.2

Pin 5-Grid No.1



Pin 6-Grid No.1

Pin 7-Heater

Pin 8-Cathode,  
Grid No.3**PUSH-PULL AF POWER AMPLIFIER — Class AB<sub>1</sub>****Maximum Ratings, Design-Center Values:**

PLATE VOLTAGE . . . . . 450 max. volts

GRID-No.2 (SCREEN-GRID) VOLTAGE . . . . . 400 max. volts

CATHODE CURRENT:

Peak. . . . . 400 max. ma

DC. . . . . 110 max. ma

GRID-No.2 INPUT . . . . . 3.5 max. watts

PLATE DISSIPATION . . . . . 25 max. watts

<sup>0</sup>: See next page.

7-58

ELECTRON TUBE DIVISION

TENTATIVE DATA 1

RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

7027



7027

## BEAM POWER TUBE

## PEAK HEATER-CATHODE VOLTAGE:

|                                          |           |       |
|------------------------------------------|-----------|-------|
| Heater negative with respect to cathode. | 200 max.  | volts |
| Heater positive with respect to cathode. | 200▲ max. | volts |

## Typical Operation with Fixed Bias:

*Values are for 2 tubes*

|                                                        |      |      |      |       |
|--------------------------------------------------------|------|------|------|-------|
| Plate Voltage . . . . .                                | 330  | 400  | 450  | volts |
| Grid-No.2 Voltage . . . . .                            | 330  | 300  | 350  | volts |
| Grid-No.1 (Control-Grid)<br>Voltage● . . . . .         | -24  | -25  | -30  | volts |
| Peak AF Grid-No.1-to-Grid-No.1<br>Voltage . . . . .    | 48   | 50   | 60   | volts |
| Zero-Signal Plate Current . . .                        | 122  | 102  | 95   | ma    |
| Max.-Signal Plate Current . . .                        | 184  | 152  | 194  | ma    |
| Zero-Signal Grid-No.2 Current .                        | 5.6  | 6    | 3.4  | ma    |
| Max.-Signal Grid-No.2 Current .                        | 18.5 | 17   | 19.2 | ma    |
| Effective Load Resistance<br>(Plate to plate). . . . . | 4500 | 6600 | 6000 | ohms  |
| Total Harmonic Distortion . . .                        | 1    | 2    | 1.5  | %     |
| Max.-Signal Power Output. . . .                        | 31.5 | 34   | 50   | watts |

## Typical Operation with Cathode Bias:

*Values are for 2 tubes*

|                                                        |      |      |       |
|--------------------------------------------------------|------|------|-------|
| Plate-Supply Voltage. . . . .                          | 400  | 380  | volts |
| Grid-No.2 Supply Voltage. . . .                        | 300  | 380  | volts |
| Cathode Resistor. . . . .                              | 200  | 180  | ohms  |
| Peak AF Grid-No.1-to-Grid-No.1<br>Voltage . . . . .    | 57   | 68.5 | volts |
| Zero-Signal Plate Current . . .                        | 112  | 138  | ma    |
| Max.-Signal Plate Current . . .                        | 128  | 170  | ma    |
| Zero-Signal Grid-No.2 Current .                        | 7    | 5.6  | ma    |
| Max.-Signal Grid-No.2 Current .                        | 16   | 20   | ma    |
| Effective Load Resistance<br>(Plate to plate). . . . . | 6600 | 4500 | ohms  |
| Total Harmonic Distortion . . .                        | 2    | 3.5  | %     |
| Max.-Signal Power Output. . . .                        | 32   | 36   | watts |

## Maximum Circuit Values:

## Grid-No.1-Circuit Resistance:●

|                                     |          |        |
|-------------------------------------|----------|--------|
| For fixed-bias operation. . . . .   | 0.1 max. | megohm |
| For cathode-bias operation. . . . . | 0.5 max. | megohm |

PUSH-PULL AF POWER AMPLIFIER — Class AB<sub>1</sub>

Grid No.2 of each tube connected to tap on  
plate winding of output transformer

## Maximum Ratings, Design-Center Values:

|                                                              |          |       |
|--------------------------------------------------------------|----------|-------|
| PLATE AND GRID-No.2 (SCREEN-GRID)<br>SUPPLY VOLTAGE. . . . . | 450 max. | volts |
|--------------------------------------------------------------|----------|-------|

0, ▲, ●: See next page.